

ELECTROMECHANICAL VALVE ASSEMBLY FOR AN INTERNAL COMBUSTION
ENGINE

FIELD OF THE INVENTION

5

This invention relates to an engine valve assembly, and particularly, to an electromechanical valve assembly for an internal combustion engine.

10 BACKGROUND OF THE INVENTION

Automotive manufacturers are currently utilizing camless intake and exhaust valve assemblies to control fluid communication in engine cylinders of internal combustion engines. The camless valve assemblies may utilize hydraulic, pneumatic, or electromechanical means to move a valve.

It is further known that varying an engine valve dwell time (i.e., the time interval a valve is open), a valve dwell position (i.e., the amount the valve is open), a valve opening rate, a valve closing rate, and an initial opening time of a valve (i.e., valve phasing) may be used to increase fuel efficiency and lower emissions. Further, the most flexible valve assemblies may be independently actuated/controlled with respect to other valve assemblies in an engine.

25 Referring to Figure 1, a known engine 10 having an engine head 12 and electromechanical valve assemblies 14, 16 is shown. The engine head 12 includes an air intake line 18 and an exhaust line 20. The valve assemblies 14, 16 control communication between the line 18, 20, respectively, with an
30 engine cylinder (not shown).

The valve assembly 14 includes a pair of solenoids 22, 24, and a valve 26. The valve 26 includes a valve stem 28 and a valve head 30. The solenoids 22, 24 are utilized to either open or close the valve 26. In particular, when the solenoid

24 is energized (and solenoid 22 is de-energized), the valve head 30 is moved axially away from a valve seat 32 to allow fluid communication between the intake line 18 and a cylinder (not shown). When the solenoid 22 is energized (and solenoid 24 is de-energized) the valve head 30 engages the valve seat 32 to prevent fluid communication between the intake line 18 and the cylinder. Thus, the known valve assembly 14 has a two-position valve 26 having either a full open state or a full closed state. As such, the valve assembly 14 has several operational disadvantages. In particular, the valve assembly 14 cannot precisely control a valve dwell time duration, a valve dwell position, a valve opening rate, a valve closing rate, valve phasing. Thus, the valve assembly 14 cannot be utilized to effectively increase fuel efficiency and lower emissions in an engine. Further, the valve assembly 14 does not provide for soft seating of the valve head 30 on the valve seat 32 under all operating conditions of the engine 10--- including temperature extremes and control strategy variations. As a result, the valve head 30 generates undesirable noise when contacting the valve seat 32.

Another known electromechanical valve assembly (not shown) includes an electric motor, a cam, and a poppet valve. The motor selectively rotates an output shaft that is connected to the cam. The cam converts that rotary motion of the output shaft to an axial motion of the poppet valve. This known valve assembly is capable of controlling a valve dwell time, a valve dwell position, a valve opening rate, and a valve closing rate. However, the known valve assembly suffers from several disadvantages. First, the valve assembly requires a separate cam resulting in increased component and manufacturing costs. Further, the valve assembly requires a relatively large package space since a separate cam is utilized for each poppet valve.

SUMMARY OF THE INVENTION

5 The present invention provides an electromechanical valve assembly for an internal combustion engine.

10 The electromechanical valve assembly in accordance with the present invention includes a rotor centered about a first axis having a bore extending generally axially therethrough. The valve assembly further includes a stator operatively
15 disposed about the rotor for producing a torque to cause rotation of the rotor about the first axis. Finally, the valve assembly includes a valve having a valve stem and a valve head. The valve stem extends generally axially through the bore of the rotor. The valve is also configured to move
20 generally axially responsive to the rotation of the rotor to selectively engage and disengage the valve head with a valve seat of the engine. In particular, the valve stem may be threadably engaged with the rotor. Further, the valve stem may have multiple lead engagement with the rotor.

25 A control system for a linear actuated electromechanical valve assembly is also provided. The control system includes a valve controller for generating a commanded valve position signal to control the incremental axial position of the valve. The valve controller can also vary a valve operational
30 parameter. In particular, the valve operation parameter includes one or more of the following: a valve dwell time, a valve opening rate, a valve closing rate, a valve dwell position, and valve phasing. The control system also includes a position sensor that generates a signal responsive to an axial position of the valve.

A method for current recirculation (i.e., energy recovery) in electromechanical valve assemblies disposed in an internal combustion engine is also provided. The current

recirculation methodology is a regenerative method that reduces the energy requirement of electromechanical valves during actuation of the valves. The method includes providing a first electromechanical valve assembly having first and second stator phases selectively connected between a first node and ground. The method further includes providing a second electromechanical valve assembly having third and fourth stator phases selectively connected between the first node and ground. The method further includes generating a braking current in the first and second stator phases of the first electromechanical valve assembly. Finally, the method includes connecting the third and fourth stator phases of the second electromechanical valve assembly to the first node to direct the braking current into the third and fourth stator phases as an accelerating current.

The electromechanical valve assembly and the control system related thereto, represent a significant improvement over conventional valve assemblies and control systems. In particular, the inventive valve assembly and control system enable the precise control of a valve dwell time, a valve opening rate, a valve closing rate, a valve dwell position, and valve phasing. As a result, the inventive valve assembly allows for increased fuel efficiency and lower emissions in an engine as compared with conventional valve assemblies.

Further, the position of the valve head may be accurately controlled for soft seating with a valve seat---resulting in reduced engine noise. Still further, the valve assembly may be packaged in a relatively small package volume allowing automotive designers increased flexibility in placement of the engine. Finally, the inventive method of current recirculation provides for decreased electrical energy consumption by the inventive valve assembly as compared with conventional electromechanical valve assemblies.

These and other features and advantages of this invention will become apparent to one skilled in the art from the following detailed description and the accompanying drawings illustrating features of this invention by way of example.

5

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is a schematic of an engine having two conventional electromechanical valve assemblies.

10

Figure 2 is a schematic and block diagram of an automotive vehicle having an engine, an engine control system, and a power distribution system in accordance with the present invention.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
219

Figure 8 is a schematic and block diagram of a magneto-strictive sensor in accordance with the present invention.

Figures 9A-9E are signal schematics illustrating signals
5 in the magneto-strictive sensor shown in Figure 8.

Figure 10 is a schematic illustrating a sonic wave propagating through a sonic conduit to a stress boundary in the conduit.

Figure 11 is a schematic illustrating a sonic wave being reflected in a sonic conduit from a stress boundary in the conduit.

Figure 12 is a flow chart illustrating a method for determining a rotational position of an object in accordance with the present invention.

Figure 13 is a schematic of an electromechanical valve assembly in accordance with a second embodiment of the present invention.

Figure 14 is a flowchart illustrating a method for determining an axial position of an object in accordance with
25 the present invention.

Figure 15 is a circuit diagram illustrating a commutation circuit for controlling the electromechanical valve assemblies shown in Figures 3 and 13.

Figures 16A-16E are signal schematics of control signals generated by the commutation circuit shown in Figure 15.

Figures 17A-17C are signal schematics of valve operational parameters during an actuation of an intake valve.

Figures 18A-18C are signal schematics illustrating current recirculation in electromechanical valve assemblies in accordance with the present invention.

Figure 19 is a flowchart illustrating a method for current recirculation in electromechanical valve assemblies in accordance with the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Referring now to the drawings wherein like reference numerals are used to identify identical components in the various views, Figure 2 illustrates an automotive vehicle 34 having an engine 36, an engine control system 38, and a power distribution system 40.

The engine 36 comprises an internal combustion engine. The engine 36 includes an engine head 42, an engine block 44, electromechanical valve assemblies 46, 48, a cylinder 50, a fuel injector 52, a spark plug 54, a piston 56, a connecting rod 58, and a crankshaft 60. Even though one cylinder 50 is shown in Figure 2 for purposes of clarity, the engine 36 includes a plurality of cylinders 50, each cylinder 50 having valve assemblies 46, 48, fuel injector 52, spark plug 54, piston 56, and connecting rod 58.

The engine head 42 is conventional in the art and defines an intake line 62 and an exhaust line 64. The engine head 42 is mounted to the engine block 44 and is configured to hold the valve assemblies 46, 48, the spark plug 54, and the fuel injector 52.

The engine block 44 is conventional in the art and defines each of the cylinders 50. As illustrated, the engine block 44 is configured to receive the engine head 42.

The inventive electromechanical valve assemblies 46, 48 comprise an intake valve assembly and an exhaust valve assembly, respectively. The valve assembly 46 controls fluid communication between the intake line 62 and the cylinder 50. Similarly, the valve assembly 48 controls fluid communication of exhaust gases between the cylinder 50 and the exhaust line 64. Because the valve assemblies 46, 48 are substantially similar---with the only difference being valve assembly 46 having a larger valve face surface than valve assembly 48---only the valve assembly 46 will be described in detail hereinafter.

Before describing the various components of the electromechanical valve assembly 46, the operational advantages of the valve assembly 46 will be discussed. As previously discussed, when operating intake and exhaust valves in an engine, it is advantageous to vary various valve operational parameters to increase fuel efficiency and lower exhaust emissions. Because the valve assembly 46 has a valve 70 that may be selectively moved to commanded incremental axial positions (discussed in greater detail below), the valve assembly 46 provides for the precise control of several valve operational parameters.

Referring to Figure 7, four valve operational profiles 86, 88, 90, 92 showing the various operational parameters that may be incrementally varied by the valve 70 are shown. As previously discussed, the valve assembly 46 can selectively vary the opening rate of valve 70. For example, profiles 86, 90 illustrate two different possible opening rates OR_1 and OR_2 for the valve 70. Similarly, the valve assembly 46 can selectively vary the closing rate of the valve 70. For

example, profiles 86, 90 illustrate two different possible closing rates CR_1 and CR_2 for the valve 70. Further, the valve assembly 46 can selectively vary the opening rate of the valve 70 independent of the closing rate of the valve 70, and vice versa, as shown in profile 90. Those skilled in the art will recognize that the torque and inertia of the valve 70 and the rotor 68 limits the valve opening and closing slew rates. In particular, the opening slew rate OR_{SLEW} may be determined by the following equation:

$$OR_{SLEW} = (\text{torque applied to rotor/inertia of rotor and valve})$$

The assembly 46 may further selectively vary the dwell time of the valve 70. For example, profiles 86, 88 illustrate two possible dwell times ΔT_1 and ΔT_2 , respectively, for the valve 70.

The assembly 46 can further move the valve 70 to a desired dwell position other than a full open position as shown in profile 92.

Referring to Figure 3, the valve assembly 46 includes a stator 66, a rotor 68, a valve 70, bearings 72, 74, an enclosure 76, a centering spring 78, a sensor magnet 80, and a position sensor 82.

The stator 66 is provided to produce a torque to cause rotation of the rotor 68. In the illustrated embodiment, the stator 66 and rotor 68 are configured as a brushless DC motor. However, one skilled in the art will realize that the stator 66 and rotor 68 could be configured as a switch reluctance motor or other motor configurations well known to those skilled in the art. As illustrated, the stator 66 is constructed from a plurality of laminated plates 94 stacked adjacent one another. Further, the stator 66 has a central bore 96 extending axially therethrough configured to receive the rotor 68. The illustrated stator 66 and rotor 68 comprise a three-phase (i.e., phases A, B, C) two-pole, brushless DC

motor. Further, the number of slots Q required in the stator 66 may be determined using the following equation:

$Q = q * m * p$, wherein,

q = number of slots/pole/phase,

5 m = number of phases,

p = number of poles in the stator 66.

Accordingly, a three-phase, two-pole, brushless DC motor may have twelve slots ($Q = 2 * 3 * 2 = 12$). Referring to Figures 4 and 5, the stator windings 98 may be routed in the stator slots S1-S12 to define the phases A, B, C. One skilled in the art will also recognize that the stator 66 and rotor 68 could alternately be constructed as a three-phase, four-pole brushless DC motor. Still further, the stator 66 and rotor 68 could have a higher number of poles if desired.

Referring to Figure 3, the rotor 68 is provided to drive the valve 70 in a first and a second axial direction. The rotor 68 includes a ring magnet 100 and a ballnut 102.

Referring to Figure 4, the ring magnet 100 may comprise magnet segments 104, 106, or may alternately comprise a single unitary magnet. In a preferred embodiment, the number of magnet segments of the magnet 100 is equal to the number of poles of the stator 66. Further each magnet segment has a flat inner surface that rests against a corresponding facet defined by an outer surface of the ballnut 102. As
25 illustrated, the ring magnet 100 is fixedly attached around the ballnut 102 and may be glued to the ballnut 102.

Referring to Figure 3, the ballnut 102 is provided to engage and drive the valve 70. The ballnut 102 is conventional in the art and may be constructed from a plurality of ferromagnetic materials including steel or iron.
30 The ballnut 102 includes a cylindrical body portion 108 and mounting arms 110, 112.

The cylindrical body portion 108 has a central bore 114 configured to receive the valve 70 therein. The body portion 108 has a helical groove 116 separated by a land portion 118. The body portion 108 further includes a return channel 120 for recirculating a train of abutting load ball bearings 122 that travel in the groove portions 116. The return channel 120 may comprise an internal U-shaped channel machined within the body portion 108. The recirculation of the bearings 122 will be discussed in greater detail hereinbelow.

The mounting arms 110, 112 are provided to rotatably support the rotor 68 about an axis 122. The mounting arm 110 is attached to a lower end of the ballnut 102 and is further attached to the bearing 72. The mounting arm 112 is attached to an upper end of the ballnut 102 and is further attached to the bearing 74. Thus, the rotor 68 may rotate in either a clockwise or counter-clockwise direction about the axis 122.

The valve 70 is provided to selectively engage or disengage a valve seat 124. The valve 70 may be constructed from a plurality of materials including, for example, case hardened steel or ceramics such aluminum nitride. The material used for constructing the valve 70 preferably has a relatively low mass so that the valve 70 may be easily accelerated. The valve 70 includes a valve stem 126, a valve head 84, and an anti-twist guide 128.

The valve stem 126 has a helical groove 130 that is separated by a land portion 132. The helical groove 130 has the same pitch as the helical groove 116 of the ballnut 102. Accordingly, the helical grooves 116, 130 form a raceway between the rotor 68 and the valve 70. Upon rotation of the rotor 68, the ball bearings 122 travel in the helical grooves 116, 130 and are recirculated in the raceway by the return channel 120. Referring to Figure 6, the helical groove 130 of the valve stem 126 has a thread or groove pitch P. The

relationship between the rotational position θ_m of the rotor 68 and the axial position of the valve 70 is defined by the following equation:

$$\theta_m = (2\pi/P) * Z; \text{ wherein,}$$

5 P = pitch of the helical grooves 116, 130,

 Z = axial position of the valve 70

In a constructed embodiment, the thread pitch P is set equal to a maximum valve stroke Z_{MAX} . Accordingly, one rotation of the rotor 68 results in the valve 70 moving an axial distance equal to the maximum valve stroke Z_{MAX} . In alternate embodiments of the valve 70 and the rotor 68, multiple rotations of the rotor 68 may be utilized to move the valve 70 to a maximum valve stroke Z_{MAX} . The valve stroke Z_{MAX} is typically 8 mm, although the valve assembly 46 may be configured to have a valve stroke greater than or less than 8 mm.

During installation of the valve 70 in the valve assembly 46 and the engine 36, the valve stem 126 may be inserted through an aperture 123 in the engine head 42. Further, the rotor 68 may have a cylindrical cardboard section (not shown) disposed in the bore 114. The cardboard section is utilized to hold the ball bearings 122 in the return channel 120 prior to attaching the rotor 68 to the valve stem 126. During attachment of the valve stem 126 to the rotor 68, the rotor 68 is threadably received by the valve stem 126, which forces the cardboard section out of the bore 114. Further, the ball bearings 122 travel in the raceway defined by the grooves 116 and 130.

An alternate embodiment of the rotor 68 and the valve 70 may also be utilized. In particular, the body portion 108 of the rotor 68 may include a second helical groove (not shown) extending alongside groove 116. Further, the valve stem 126 of the valve 70 may include a second helical groove (not

shown) extending alongside the groove 130. The two additional helical grooves form a second raceway (not shown) for a second set of ball bearings to travel therein. Further, the second set of ball bearings are recirculated in the second raceway via a second return channel (not shown). By utilizing a second set of recirculating ball bearings, the effect of side loading forces on the valve 70 may be reduced.

The spring 78 is provided to center the valve 70 at a predetermined axial position when the engine 36 is shutdown (and the stator 66 is de-energized). This initial reference position may be measured by a position sensor and may be stored by a valve controller 134 for calculating the relative position of the valve 70 with respect to the initial position. As illustrated, the spring 78 is connected between one end of the valve stem 126 and the enclosure 76. Referring to Figure 3, the spring 78 may be selected to center the valve 70 at any desired initial between the 0 valve position and the Z_{MAX} valve position. For example, each of the springs 78 may be pre-loaded to each valve 70 in a closed position (i.e., 0 valve position)---to minimize a cranking torque of an integrated starter/alternator of the engine 36.

As previously discussed, the valve head 84 is configured to engage the valve seat 124 of the engine 36. As illustrated, the valve head 84 may be integrally connected to the valve stem 126.

The anti-twist guide 128 is provided to prevent rotational movement of the valve 70 about the axis 122. The anti-twist guide 128 may comprise a radially extending engagement portion connected to the valve stem 126 that engages a slot or keyway (not shown) in the engine head 42. Preventing rotation of the valve 70 provides several advantages. First, the valve 70 will less likely deteriorate the valve seat 124 if the valve 70 does not rotate while

engaging the valve seat 124. Second, the axial position of the valve 70 may be accurately determined if the valve 70 does not rotate relative to the rotation of the rotor 68.

5 The bearings 72, 74 are provided to allow rotation of rotor 68 relative to the stator 66 and are conventional in the art. As illustrated, the bearing 74 is connected between a mounting arm 112 of the rotor 68 and an upper mounting arm 136 of the enclosure 76. Similarly, the bearing 72 is connected between the mounting arm 110 of the rotor 68 and a lower mounting arm 138 of the enclosure 76.

10 The enclosure 76 is provided to enclose and protect the stator 66, the rotor 68, and portions of the valve 70. Further, the enclosure 76 is mounted to the engine head 42. The enclosure 76 includes an outer wall 140, an upper mounting arm 136, and a lower mounting arm 138. The outer wall 140 defines a bore 142 for the valve stem 126 to extend therethrough.

15 The sensor magnet 80 is provided to indicate the rotational position of the rotor 68. As illustrated, the magnet 80 may be connected to a mounting arm 112 of the rotor 68.

20 The position sensor 82 is provided to determine the rotational position θ_m of the rotor 68 and an axial position Z of the valve 70 in accordance with the present invention. The position sensor 82 may comprise a magneto-strictive sensor that has a relatively small package space as compared with conventional position sensors. Referring to Figure 8, the magneto-strictive sensor 82 includes a sonic conduit 144, a sensor controller 146, an oscillator 148, a sonic wave generator 150, a sonic wave receiver 152, and a temperature sensor 154.

25 The sensor controller 146 is provided to calculate a rotational position θ_m of the rotor 68 and an axial position Z

of the valve 70. The controller 146 may comprise either discrete circuits or a programmable microcontroller. As illustrated, the sensor controller 146 is electrically connected to the oscillator 148, the sonic wave receiver 152, and the temperature sensor 154. The sensor controller 146 is configured to generate a transmit signal V_{TR} at a predetermined frequency that is transmitted to the oscillator 148. In a constructed embodiment, the transmit signal V_{TR} is transmitted at a frequency of 100 Khz. The sensor controller 146 receives the temperature signal V_{TEMP} , the received signal V_R , (explained in detail hereinafter) and the oscillator signal V_{OSC} (explained in detail hereinafter), and calculates the rotational position θ_M of the rotor 68 and an axial position Z of the valve 70.

The oscillator 148 is provided to generate an oscillator signal V_{OSC} responsive to the transmit signal V_{TR} . The oscillator 148 may comprise a conventional voltage controlled oscillator or discrete circuits. As illustrated, the oscillator 148 is electrically connected in series between the sensor controller 146 and the sonic wave generator 150. Referring to Figures 9A and 9B, the oscillator 148 receives a transmit signal V_{TR} at a high logic level and generates an oscillator signal V_{OSC} at a 1 Mhz frequency responsive thereto. Those skilled in the art will recognize that the frequency of the transmit signal V_{TR} and the oscillator signal V_{OSC} may be greater than or less than 100 Khz or 1Mhz, respectively, depending upon the desired accuracy of the calculated rotational position θ_M and the axial position Z . The frequency of the oscillator signal V_{OSC} (frequency of $V_{OSC} = (1 / \Delta T_4)$) is preferably ten times greater than the frequency of the transmit signal V_{TR} (frequency of $V_{TR} = (1 / \Delta T_3)$). Further, the frequency of the transmit signal V_{TR} is preferably greater than twice the round trip travel time T_{RT} (explained in greater detail below) of the sonic wave.

The sonic wave generator 150 is provided to generate a sonic wave in the sonic conduit 144. The sonic wave generator 150 may comprise a conventional piezoelectric transducer and is electrically connected to the oscillator 148 and is further bonded to the sonic conduit 144. The generator 150 receives the oscillator V_{osc} and generates a sonic wave (i.e., sound wave) in the conduit 144 responsive to the oscillator signal V_{osc} .

The sonic conduit 144 is provided to propagate a sonic wave in the conduit 144 around a portion of a circumference of the rotor 68. The sonic conduit 144 may comprise a metal wire or a metal strip that extends around a substantial portion of the circumference of the rotor 68 proximate to the rotor 68. The conduit 144 may be constructed from a plurality of metals, including for example, a nickel-iron alloy. In a constructed embodiment, the conduit 144 is constructed of 18 gauge wire. Referring to Figures 8 and 10, the sensor magnet 80 disposed on the rotor 68 induces a localized stress boundary 156 on the conduit 144 proximate to the magnet 80. In particular, the magnet 80 deforms the conduit 144. Accordingly, the magnet 80 and the boundary 156 are indicative of the position of the rotor 68. Accordingly, a sonic wave traveling in the conduit 144 in a first direction to the stress boundary 156, will be reflected from the boundary 156 in a second direction (opposite the first direction). The gap G in the conduit 144 ensures that each the sonic wave initially propagates in only one direction (i.e., clockwise in Figure 8) around the conduit 144 to the boundary 156.

Referring to Figure 8, the sonic wave receiver 152 is provided to generate a received signal V_r upon receipt of a sonic wave. The sonic wave receiver 152 may comprise a conventional piezoelectric transducer and is electrically connected to the sensor controller 146 and is further

connected to the conduit 144. Referring to Figures 9D and 9E, at time interval T_2 - T_3 , the receiver 152 receives the sonic wave and generates the received signal V_R responsive thereto.

5 The temperature sensor 154 generates a temperature signal V_{TEMP} indicative of the ambient air temperature around the sonic conduit 144 and valve assembly 46. The temperature sensor 154 is conventional in the art and is electrically connected to the sensor controller 146.

10 Referring to Figure 12, a method for determining a rotational position of the rotor 68 (i.e., object) utilizing the inventive position sensor 82 will be described. The method includes a step 158 of providing a sonic conduit 144 extending around a substantial portion of a circumference of the rotor 68.

15 The method further includes a step 160 of generating a sonic wave in the conduit 144 that propagates to a localized stress boundary 156 in the conduit 144 wherein the sonic wave is reflected in the conduit 144 from the boundary 156. Referring to Figures 9A, 9B, and 9C, the sensor controller 146 between the time interval T_0 - T_1 , generates a transmit signal V_{TR} at high logic level that causes the oscillator 148 to generate oscillator signals V_{osc} . The oscillator signals V_{osc} cause the sonic wave generator 150 to generate a sonic wave (i.e., vibration) in the conduit 144. The sonic wave propagates in a
25 first direction to the stress boundary 156 and is reflected from the stress boundary 156 in a second direction (opposite the first direction) back toward a sonic wave receiver 152.

Referring to Figure 12, the method further includes a step 162 of receiving the reflected sonic wave at a
30 predetermined position along the sonic conduit 144. Referring to Figures 9D and 9E, during time interval T_2 - T_3 , the sonic wave is received by the sonic wave receiver 152. In response,

the receiver 152 generates the received signal V_R that is transmitted to the sensor controller 146.

Referring again to Figure 12, the method further includes a step 164 of calculating a rotational position value θ_M of the rotor 68 and an axial position Z of the valve 70 responsive to the round trip travel time T_{RT} of the sonic wave in the conduit 144. The equations used by the sensor controller 146 to calculate the rotational position θ_M of the rotor 68 and the axial position Z of the valve will now be explained. Referring to Figure 8, the path length L may be determined utilizing the following equation:

$$L = (R * \theta_M) = (VEL(T) * T_{RT}/2); \text{ wherein,}$$

R = known radius of the sonic conduit 144,

θ_M = angular position of the sensor magnet 80,

$VEL(T)$ = velocity of the sonic wave in the sonic conduit 144 as a function of the temperature T ,

T_{RT} = round trip travel time of the sonic wave.

For purposes of illustration and simplicity, the conduit length from point P1 to point P2 is assumed to be zero.

Accordingly, the rotational position θ_M of the rotor 68 may be calculated using the following equation:

$$\theta_M = (VEL(T) / 2R) * T_{RT}$$

Further, when the rotational position θ_M of the rotor 68 is known, the axial position Z of the valve 70 may be calculated using the following equation:

$$Z = \theta_M * P / 2\pi; \text{ wherein,}$$

P = pitch of the grooves 130 in the valve stem 126.

As noted above, the velocity of the sonic wave is dependent on the temperature of the conduit 144. In particular, the following equation may be utilized to calculate the velocity sonic wave velocity:

$$VEL(T) = VEL_0 [1 + \alpha(T - T_0)]; \text{ wherein,}$$

VEL_0 = velocity of sonic wave at temperature $T = 20^\circ\text{C}$,

α = temperature coefficient of sonic conduit material,
 T_0 = 20°C
 T = measured temperature of the conduit utilizing
temperature sensor 154.

- 5 The foregoing equation for calculating VEL(T) represents a truncated Fourier expansion of non-linear velocity versus temperature relationship.

Referring to Figure 13, an electromechanical valve assembly 166 is provided that is a second embodiment of the valve 46. The valve assembly 166 is substantially the same as the valve assembly 46, except that the sensor magnet 80 has been removed and a valve 168 and a position sensor 170 are used instead of valve 70 and position sensor 82, respectively.

The valve 168 is substantially the same as the valve 70 except that a valve 168 has a bore 172 extending axially into the valve 168.

The position sensor 170 is provided to calculate an axial position Z of the valve 168. The position sensor 170 is substantially the same as the position sensor 82 and includes the sensor controller 146, the oscillator 148, the sonic wave generator 150, the sonic wave receiver 152, and the temperature sensor 154. However, the position sensor 170 utilizes a flexible lead wire 174 and a sonic conduit 176 instead of the sonic conduit 144. As illustrated, the sonic conduit 176 may comprise a longitudinally extending metal wire or a metal bar that is disposed in the bore 172 of the valve 168. The conduit 176 may be constructed from a plurality of metals, including for example, a nickel-iron alloy. Further, the ring magnet 100 of the rotor 68 induces a localized stress boundary 178 in the conduit 176.

The axial distance D from a first end of the conduit 176 to the stress boundary 178 is indicative of the axial position of the valve 168. In particular, the distance D (and the

round trip travel time T_{RT} of a sonic wave) will increase as valve 168 incrementally moves in a first axial direction (downward in Figure 13). Similarly, the distance D (and the round trip travel time T_{RT} of the sonic wave) will decrease as the valve 168 moves in a second axial direction (upward in Figure 13) opposite the first axial direction. Accordingly, the sensor controller 146 may calculate the axial position Z of the valve 168 utilizing the following equation:

$$Z = D = (\text{VEL}(T) * T_{RT}/2).$$

For purposes of illustration and simplicity, the length of the lead wire 174 is assumed to be equal to a zero length.

Referring to Figure 14, a method for determining an axial position of a valve 168 utilizing the position sensor 170, will be described. The method includes a step 180 of providing a sonic conduit 176 extending generally axially on or integral with the valve 168. The method further includes a step 182 of generating a sonic wave in the conduit 176 that propagates to a localized stress boundary 178 wherein the wave is reflected from the boundary 178. The method further includes a step 184 of receiving the reflected sonic wave at a predetermined position along the conduit 176. Finally, the method includes a step 186 of calculating an axial position Z of the valve 168 responsive to the travel time of the sonic wave in the conduit 176.

Referring to Figure 2, the remaining elements of the engine 36 will be described. As previously discussed, the engine 36 includes the fuel injector 52. The fuel injector 52 selectively provides fuel to one or more cylinders 50 and is conventional in the art. In particular, each fuel injector 52 delivers a predetermined amount of fuel into one or more cylinders 50 responsive to a fuel injector control signal V_{FI} generated by an engine controller 188.

The spark plug 54 is provided to ignite the fuel in the cylinder 50 responsive to an ignition control signal V_i generated by the engine controller 188. When the fuel is ignited in the cylinder 50, the piston 56 drives the crankshaft 60 via the connecting rod 58.

Referring again to Figure 2, the engine control system 38 is provided to control the operation of the engine 36 in accordance with the present invention. The engine control system 38 includes a valve controller 134, an engine controller 188, a crankshaft position sensor 190, and the valve position sensor 82.

The valve controller 134 is a bi-directional controller that can control the incremental movement of valves in both axial directions. For purposes of discussion it will be assumed that each of the valve assemblies 46, 48 includes a valve 70 and a position sensor 82. As illustrated, the valve controller 134 receives a rotational position value θ_m and an axial position value Z from the position sensor 82, and a crankshaft position signal V_{cs} from the crankshaft position sensor 190. Further, the valve controller 134 receives operational parameters from the engine controller 188 for each valve 70 via a communication bus 192. The communication bus may comprise a CAN (i.e., controller area network) bus operating at a bus speed of 1 megabit/second. The valve operational parameters include a valve dwell time, a valve opening rate, a valve closing rate, and valve phasing information. In response to the foregoing signals and parameters for each valve 70, the valve controller 134 generates a commanded valve position current I_{cp} ---for each valve assembly 46, 48---to selectively control the axial position of each valve 70.

Referring to Figure 15, a more detailed schematic of the valve controller 134 is illustrated. In particular, the valve

controller 134 contains a conventional commutation circuit 194 for each valve assembly 46, 48 in the engine 36. For example, when engine 36 has four-cylinders and eight valve assemblies (four intake valve assemblies 46 and four exhaust valve assemblies 48), the valve controller 134 would have eight commutation circuits 194 to control the eight valve assemblies. Each of the circuits 194 would be connected between a node 196 (connected to a positive terminal of the battery 234) and system ground. Each commutation circuit 194 includes switches 198, 200, 202, 204, 206, 208, a capacitor 210, a resistor 212, and a commutation module 214.

Switches 198, 200, 202, 204, 206, 208 are provided to selectively energize the phases A, B, C of the stator 66. Switches 198, 200, 202, 204, 206, 208 are conventional in the art and may comprise either MOSFET transistors, IGBT transistors in either planar or trench structure, or bipolar transistors. Switches 198, 200 are connected in series between nodes 196, 216 and have an intermediate node 218 connected to phase A. Similarly, switches 202, 204 are connected in series between nodes 196, 216 and have an intermediate node 220 connected to phase B. Further, switches 206, 208 are connected in series between nodes 196, 216 and have an intermediate node 222 connected to phase C.

The capacitor 210 is provided to ground transient voltage spikes which could damage the switches 198, 200, 202, 204, 206, 208. As illustrated, the capacitor 210 is connected between the node 196 and ground.

The resistor 212 is provided to sense the current flow through the switches 198, 200, 202, 204, 206, 208 and to prevent damage thereto. The resistor 212 is connected between the node 216 and ground.

The commutation module 214 is provided to generate control signals to control the energization of the phases A,

B, C of the stator 66. In particular, the commutation module 214 receives either the rotational position value θ_m or the axial position Z from the position sensor 82. In response, the commutation module generates commutation signals CS1, CS2, CS3, CS4, CS5, CS6 to selectively energize the phases A, B, C. Referring to Figure 16, commutation signals CS1, CS2, CS3, CS4, CS5, CS6 are shown for energizing the phases A, B, C pairwise to move the rotor 68 one complete revolution (i.e., 360 mechanical degrees) are shown.

Referring to Figures 17B and 17C, a valve operational profile 215 (illustrating a complete operational cycle of a valve 70) and a corresponding commanded valve position current I_{cp} effectuating the valve cycle is shown. Figure 17A illustrates the pressure P within a cylinder 50 as the valve 70 progresses through the valve cycle. At crankshaft angle $\theta_{cs} = 135^\circ$, the valve controller 134 commands the valve 70 to move to an open position to allow exhaust gases in the cylinder 50 to exit the cylinder 50. In particular, the valve controller 134 increases the commanded valve position current I_{cp} ---in a positive direction---that results in the valve accelerating toward a full open position. As the valve 70 opens, the exhaust gas exits the cylinder 50 resulting in a decreasing cylinder pressure.

At crankshaft angle $\theta_{cs} = 150^\circ$, when the valve 70 is moving to the full open position, the valve controller 134 decreases the commanded position current I_{cp} . When the current I_{cp} reverses direction as a negative or braking current, the valve 70 de-accelerates prior to reaching the full open position.

At crank shaft angle $\theta_{cs} = 160^\circ$, when the valve 70 has reached to the full open position, the controller 134 commences to decrease the negative current I_{cp} until it reverses direction as a positive or holding current. Afterward, the controller 134 maintains the positive current

I_{CP} at an dwell current level for a desired dwell time. The holding current is necessary to counteract forces acting the valve 70 generated by the spring 78 and the cylinder gas pressure.

5 In response, the valve 70 is maintained at a full open position. Further, the cylinder pressure remains at a relatively constant pressure level.

At crankshaft angle $\theta_{CS} = 185^\circ$, the controller 134 commands the valve 70 to move to a closed position. In particular, the
10 controller 134 decreases the current I_{CP} until it reverses direction as a negative current. In response, the valve 70 accelerates toward a full closed position.

At crankshaft angle $\theta_{CS} = 190^\circ$, the controller 134 decreases negative current I_{CP} until it reverses direction as a positive current to de-accelerate the valve 70 prior to the
15 valve 70 reaching the full closed position. Accordingly, the de-acceleration of the valve 70 provides for soft seating of the valve 70 with the valve seat 124. Thus, engine noise may be reduced.

Referring to Figure 2, the engine controller 188 is provided to control the operation of the engine 36. The engine controller 188 may comprise either discrete circuits or a programmable microcontroller. The controller 188 receives a crankshaft position signal V_{CS} and generates the fuel injector
20 control signal V_{FI} responsive thereto. As previously discussed, the controller 188 also calculates valve operational parameters for each valve including a dwell time duration, an opening rate, a closing rate, a dwell position, and phasing information. Further, the controller 188
25 transmits these operational parameters to the valve controller 134 via a communication bus 192.

30 The crankshaft position sensor 190 generates a crankshaft position signal V_{CS} indicative of the rotational position of

the crankshaft 60. The sensor 190 is conventional in the art and may comprise a Hall Effect Sensor or a variable reluctance sensor. The engine controller 188 may receive the crankshaft position signal V_{cs} and derive the crankshaft angle θ_{cs} responsive thereto.

Referring to Figure 19, a method for current recirculation (i.e., energy recover) in the electromechanical valve assemblies 46, 48 is provided. Those skilled in the art will recognize that current recirculation during operation of the intake and exhaust valve assemblies 46, 48, will result in increased engine efficiency. In particular, the method utilizes a braking current---generated when a valve is closing in the exhaust valve assembly 48---as an accelerating current to open a valve in the intake valve assembly 46. It should be understood, however, that the method could be implemented with any two valve assemblies in the engine 36 where one valve assembly is closing a valve and a second valve assembly is simultaneously opening a valve.

Referring to Figures 15 and 19, the method for current recirculation includes a step 224 of providing an exhaust valve assembly 48 having stator phases D and E selectively connected between a node 196 and ground. The method further includes a step 226 of providing an intake valve assembly 46 having stator phases A and B selectively connected between node 196 and ground.

The method further includes a step 228 of generating a braking current I_{cp} in phases D and E of the exhaust valve assembly 48. Referring to Figures 18A and 18B, between crankshaft angles θ_0 and θ_2 , the exhaust valve assembly 48 is closing a valve and is generating a braking current I_{cp} (i.e., a negative current). Referring to Figure 15, when the phases D and E of valve assembly 48 are generating a negative current

I_{CP} (i.e., $-I_{CP}$), the current flows through the node 196 common to all commutation circuits 194.

Finally, the method further includes a step 230 of connecting the stator phases A, B of the intake valve assembly 46 to the node 196 to direct the braking current I_{CP} into stator phases A, B as an accelerating current I_{CP} . Referring to Figures 18A, 18B, and 18C, between crankshaft angles θ_0 and θ_2 , the intake valve assembly 46 utilizes the braking current I_{CP} generated by the exhaust valve assembly 48 to open the valve 70.

Referring to Figure 2, a power distribution system 40 is provided for the engine control system 38 and the engine 36. The power distribution system 40 includes an alternator 232, a battery 234, a battery 236, and a DC/DC converter 238.

The alternator 232 is provided to maintain the state of charge in the battery 234 and the battery 236 at an adequate operational level. The alternator 232 is conventional in the art and may comprise a high power density 42 Vdc permanent-magnet enhanced water-cooled unit. Further, the alternator 232 may have a power rating of 2.5-3.5 Kilowatts to provide adequate power for the valve assemblies 46, 48 and for the remaining electrical components of the vehicle 34. The alternator 232 is driven by the crankshaft 60 and generates a current that is applied to the battery 234 and the DC/DC generator 238.

The battery 234 provides a 42 Vdc voltage to the valve controller 134 and is conventional in the art. It should be understood that the valve assemblies 46, 48 operate more efficiently utilizing a 42 Vdc voltage versus a 12 Vdc voltage. In particular, the valve controller 134 can generate a commanded valve position current I_{CP} at a lower current level utilizing the 42 Vdc voltage as compared with utilizing a 12 Vdc voltage.

The battery 236 provides a 12 Vdc voltage to the engine controller 188 and is conventional in the art. The battery 236 is connected to the conventional DC/DC converter 238 which supplies a 12 Vdc charging voltage to the battery 236.

5 The electromechanical valve assembly 46 and the engine control system 38 represent a significant improvement over conventional valve assemblies and engine control systems. In particular, the valve assembly 46 and engine control system 38 enables the precise control of a valve dwell time, a valve
10 opening rate, a valve closing rate, a valve dwell position, and valve phasing. As a result, the inventive valve assembly 46 allows for increased fuel efficiency and lower emissions in the engine 36 as compared with conventional valve assemblies. Further, the position of the valve 70 (and the valve head 84)
15 may be accurately controlled for soft seating with a valve seat---resulting in reduced vehicle noise. Still further, the valve assembly 46 may be packaged in a relatively small package volume allowing automotive designers increased flexibility placement of the engine 36. Finally, the
20 inventive method of current recirculation provides for decreased electrical energy consumption by the valve assemblies 46, 48 providing a longer operational life for a vehicle battery.

25 While the invention has been particularly shown and described with reference to the preferred embodiments thereof, it is well understood by those skilled in the art that various changes and modifications can be made in the invention without departing from the spirit and the scope of the invention.